

**MAXIMUM NUMBER OF FIXTURES PER CIRCUIT BREAKER (MCB)**

	MCB 16A TYPE B	MCB 16A TYPE C
<b>T5</b>		
1x T5 14/21/28/35W HE EL. GEAR	28	48
1x T5 24/39/54/49W HO EL. GEAR	28	48
1x T5 80W HO EL. GEAR	15	25
2x T5 14/21/28/35W HE EL. GEAR	28	48
2x T5 24/39/54/49W HO EL. GEAR	20	34
2x T5 80W HO EL. GEAR	12	20
4x T5 14W HE EL. GEAR	28	48
4x T5 24W HO EL. GEAR	12	20
<b>CFL</b>		
1x TC-DE 26W EL. GEAR	28	48
2x TC-DE 18/26W EL. GEAR	28	48
2x TC-TE 26/32/42W EL. GEAR	12	20
<b>HID</b>		
HST-TG 50W EL. GEAR	24	41
HST-TG 100W EL. GEAR	14	24
HIT-TM 20W EL. GEAR	24	41
HIT-TM 35W EL. GEAR	24	41
HIT (-TC) 35W EL. GEAR	24	41
HIT (-TC) 50W EL. GEAR	24	41
HIT (-TC) 70W EL. GEAR	20	34
HIT 100W EL. GEAR	17	12
HIT 150W EL. GEAR	6	10
HIT MW 210W EL. GEAR	4	6

	MCB 16A TYPE B	MCB 16A TYPE C
<b>LED</b>		
LED P 1100 HO	24	40
LED P 2000 HO	24	40
LED P 2500 HO	24	40
LED P 3000 HO	24	40
LED A 3500 HO	26	44
LED A 4500 HO	26	44
LED A 3000/CW HO	24	40
LED 1900/MEAT	11	22
LED 2750/GOLD	11	22
LED DLMi 1100	137	232
LED DLMi 2000	73	124
1x LED 1250	115	115
2x LED 1250	23	46
3x LED 1250	23	46
4x LED 1250	12	24
1x LED 3000	23	46
2x LED 3000	12	24
3x LED 3000	8	14
4x LED 3000	6	12
BGV 1500 LED 35W 4200LM	12	24
BGV 1500 LED 62W 7000LM	12	24
BGVL 1500 LED 33W 4300LM	12	24
BGVL 1500 LED 41W 5200LM	12	24
BGVL 1500 LED 53W 6300LM	12	24
BGLB 1500 LED 33W 4800LM	19	31
BGLB 1500 LED 41W 5700LM	12	24
BGLB 1500 LED 53W 7000LM	19	31
BGLDA 1500 LED 33W 4800LM	19	31
BGLDA 1500 LED 41W 5700LM	12	24
BGLDA 1500 LED 53W 6900LM	19	31